

Many times all you need is a simple device to route Stereo Audio over long distances, but want a high quality, fully shielded, Balanced-Line for best hum rejection. This is it. With the addition of a 2-conductor pass-thru connection, you can also do IR or relay activation.

These units, sold and used in pairs, are passive and require no power supply. They are good for 100 Meters of CAT5 or CAT6 UTP

cable.





- 1. RCA stereo input /ouput
 - 2. 1/8" mini for IR pass-thru
 - 3. Rugged shielded aluminum enclosure brushed anodized surface
- 4. RJ-45 jack for UTP connection

HDS-12 Specifications

CONNECTIONS: Stereo Line Level Audio, RCA (Male)

type connectors (2)

2-Conductor, 1/8" (Mini Phone Male) for

IR Pass-Thru (1)

RJ-45 Jack for UTP Connection (1)

CASE STYLE: Extruded Aluminum, Fully shielded and

grounded

FREQ. RESP.: 20-20KHz +- 3dB, .1%THD@1KHz/1V p-p

IR: IR Passive connection

WARRANTY: 3 Years Parts and Labor

INCLUDED: (2) SB-1 units per box (matched pair)

(1) Dual-Female mini-jack adapter



Contributor Member of HDBase-T Alliance Authorized HDMI Adopter 781-769-6410 Norwood, MA 02062 USA www.transformativeengineering.com